

INSTRUCTION MANUAL

SB-5684K

8x4 HDMI Matrix Routing Switcher

4K|2K
CAPABLE



SHINYBOW™ USA
MULTIMEDIA AUDIO AND VISUAL



SAFETY INFORMATION



1. To ensure the best results from this product, please read this manual and all other documentation before operating your equipment. Retain all documentation for future reference.
2. Follow all instructions printed on unit chassis for proper operation.
3. To reduce the risk of fire, do not spill water or other liquids into or on the unit, or operate the unit while standing in liquid.
4. Make sure power outlets conform to the power requirements listed on the back of the unit. Keep unit protected from rain, water and excessive moisture.
5. Do not attempt to clean the unit with chemical solvents or aerosol cleaners, as this may damage the unit. Dust with a clean dry cloth.
6. Do not use the unit if the electrical power cord is frayed or broken. The power supply cords should be routed so that they are not likely to be walked on or pinched by items placed upon or against them, paying particular attention to cords and plugs, convenience receptacles, and the point where they exit from the appliance.
7. Do not force switched or external connections in any way. They should all connect easily, without needing to be forced.
8. Always operate the unit with the AC ground wire connected to the electrical system ground. Precautions should be taken so that the means of grounding of a piece of equipment is not defeated.
9. AC voltage must be correct and the same as that printed on the rear of the unit. Damage caused by connection to improper AC voltage is not covered by any warranty.
10. Turn power off and disconnect unit from AC current before making connections.
11. Never hold a power switch in the "ON" position.
12. This unit should be installed in a cool dry place, away from sources of excessive heat, vibration, dust, moisture and cold. Do not use the unit near stoves, heat registers, radiators, or other heat producing devices.
13. Do not block fan intake or exhaust ports. Do not operate equipment on a surface or in an environment which may impede the normal flow of air around the unit, such as a bed, rug, carpet, or completely enclosed rack. If the unit is used in an extremely dusty or smoky environment, the unit should be periodically "blown free" of foreign dust and matter.
14. To reduce the risk of electric shock, do not remove the cover. There are no user serviceable parts inside. Refer all servicing to qualified service personnel. There are no user serviceable parts inside.
15. When moving the unit, disconnect input ports first, then remove the power cable; finally, disconnect the interconnecting cables to other devices.
16. Do not drive the inputs with a signal level greater than that required to drive equipment to full output.
17. The equipment power cord should be unplugged from the outlet when left unused for a long period of time.
18. Save the carton and packing material even if the equipment has arrived in good condition. Should you ever need to ship the unit, use only the original factory packing.
19. Service Information Equipment should be serviced by qualified service personnel when:
 - A. The power supply cord or the plug has been damaged.
 - B. Objects have fallen, or liquid has been spilled into the equipment.
 - C. The equipment has been exposed to rain
 - D. The equipment does not appear to operate normally, or exhibits a marked change in performance
 - E. The equipment has been dropped, or the enclosure damaged.

TABLE OF CONTENTS

4K2K HDMI MATRIX SWITCHER SERIES

Thank you for purchasing the SB-5684K 4K2K HDMI Matrix Routing Switch. You will find this unit easy to install and highly reliable but it is essential that you read this manual thoroughly before attempting to use the 8x4 4K2K HDMI matrix switcher.

CONTENTS

INTRODUCTION	1
FEATURES & CONTENTS.....	2
SPECIFICATIONS	3
FRONT PANEL	4
REAR PANEL	10
REMOTE CONTROL	12
RS-232 / ETHERNET SERIAL INTERFACE	14
EDID FUNCTIONS	15
IR EXTENDER	18
TYPICAL APPLICATION	19

INTRODUCTION

The SB-5684K is a professional 8x4 matrix routing switch. Supporting (8) HDMI Inputs and (4) HDMI outputs with (1) Preview output. The SB-5684K is based on HDMI standards and supports full resolution HDMI video with (7) embedded EDID so there is no signal degradation. High Definition digital signals can be selected and distributed from any of the (8) Inputs to the (4) outputs +(1) preview output. The switcher is fully CEC and HDCP 1.3 certified with HDMI 1.4a, 4K2K@30Hz, DVI 1.0, 3D formats. Wide frequency range of 25MHz~340 MHz for full HD and supports UXGA/WUXGA/DVI 1920x1200 resolutions to any HD display. The SB-5684K has 1x HDMI connector per Input, effectively making this an (8) in x (4+1) out switcher. The EDID management can be selected between (7) different modes. Control is provided via front panel push buttons, IR remote, RS-232 or TCP/IP (not a web-browser). A RS-232 Windows GUI interface is provided for matrix routing control (Windows only).

SAFETY PRECAUTIONS

Please read all instructions before attempting to unpack, install or operate this equipment and before connecting the power supply. Please keep the following in mind as you unpack and install this equipment:

- Always follow basic safety precautions to reduce the risk of fire, electrical shock and injury to persons.
- To prevent fire or shock hazard, do not expose the unit to rain, moisture or install this product near water.
- Never spill liquid of any kind on or into this product.
- Never push an object of any kind into this product through any openings or empty slots in the unit, as you may damage parts inside the unit.
- Do not attach the power supply cabling to building surfaces.
- Use only the supplied power supply unit (PSU). Do not use the PSU if it is damaged.
- Do not allow anything to rest on the power cabling or allow any weight to be placed upon it or any person walk on it.
- To protect the unit from overheating, do not block any vents or openings in the unit housing that provide ventilation and allow for sufficient space for air to circulate around the unit.

DISCLAIMERS

The information in this manual has been carefully checked and is believed to be accurate. We assume no responsibility for any infringements of patents or other rights of third parties which may result from its use.

We assume no responsibility for any inaccuracies that may be contained in this document. We make no commitment to update or to keep current the information contained in this document.

We reserve the right to make improvements to this document and/or product at any time and without notice.

COPYRIGHT NOTICE

No part of this document may be reproduced, transmitted, transcribed, stored in a retrieval system, or any of its part translated into any language or computer file, in any form or by any means — electronic, mechanical, magnetic, optical, chemical, manual, or otherwise — without express written permission and consent

© Copyright 2015. All Rights Reserved.
Version 1.1 OCT 2015
5684K-20150822-002

TRADEMARK ACKNOWLEDGMENTS

All products or service names mentioned in this document may be trademarks of the companies with which they are associated.

FEATURES

FEATURES

- (8) HDMI source devices matrix switched to (4) HDMI +(1) output #1 preview output destinations
- HDMI digital video w/ embedded HDCP, DVI formats and CEC/HDCP 1.3 compliant
- Worldwide EDID control modes for HDMI full 4K2K (24/30 Hz) HD video resolutions
- Wide frequency range of 25MHz ~ 340MHz, Supports HDMI 4K2K, 1.4a 3D formats
- Wide range of HD resolutions from PC XGA to WUXGA 1920x1200 and HDTV/DTV HDMI resolutions 480i/480p, 576i/576p, 720p, 1080i/p & 4K2K (24/30Hz)
- Compatible with all HDMI source devices, PC monitors, Plasma HD display, HDTV and audio receivers or audio amplifiers
- Digital video TMDS formats resolutions up to 4K2K with Deep color 36-bit
- Using the build-in booster, each HDMI Output port is capable of driving cable lengths of up to 1080p up to 98 feet (30M) & 4K2K up to 66 ft (20M)
- Digital Audio Supports: Dolby TrueHD, Dolby Digital, Dolby Digital Plug/ex, DTS, DTS-HD, DTS-HD Master, DTS-EX, PCM, PCM2, LPCM2
- Various User Interface control:
 - Windows based GUI control via RS-232 interface 2000/XP/WIN7-32/WIN7-64/WIN8
 - Front panel push button
 - IR wireless remote control
 - Ethernet switch control
 - Third party RS-232 controller (via simple ASCII)
- Supports (7) world wide control function keys: Full function front panel controls: ALL / OFF / EDID / LOCK / RECALL / MEMORY / ENTER
- Supports EDID Modes:
 - Embedded EDID Modes: FSS/ H24-3D/ H24-3D-M/ H36-3D/ H36-3D-M/ 4K2K-3D / DVI-D 1920x1200-60Hz
 - External Modes: Learning mode-1 (Single Learning) & Learning mode-2 (Multiple Learning)
- Automatic scanning of input & output status via LCM display on the front panel
- Supports IR Remote and IR Extenders for a distance of up to ~ 984 feet (300M) Maximum
- Supports Universal power adaptor AC100V~AC240V, 50/60Hz

The switcher will remember that last state during a power cycle. When power is removed and resorted, the last configuration will be invoked.

PACKAGE CONTENTS

Check that you have the following components;

- SB-5684K Matrix Switcher
- RS-232 V2.0 / Ethernet V2.0 Protocol Instructions
- Master wireless IR Remote Control (SW-5684K)
- 19 inch Ear mount bracket (Part # 1U-440L)
- SB-100 IR Extender distance ~984 feet (300M) Receiver set
- CD Contents : Manual, Windows GUI, ISP V1.0 Windows driver
- RS-232 Cable 6 feet (2M)
- ISO Screws
- Users Guide
- Power Supply Input : Worldwide Universal 100~240 VAC, AC 50/60Hz



SPECIFICATIONS


SPECIFICATIONS

- **Type of HDMI Switcher:** (8) Inputs to (4+1) Outputs HDMI Matrix Routing Switch
- **HDMI Support:** HDMI 4K2K@30Hz, 1080p@60Hz, H36-bit Deep color, 3D of HDMI V1.4 formats
- **HDCP / CEC Support:** HDCP 1.3 Compliant, CEC Compliant
- **Video Bandwidth:** Wide frequency 25MHz ~ 340Mhz
- **Digital Video Support:** HD: 480i/ 480p/ 720p/ 1080i/p and 4K2K up to 36bit deep color
- **Video Inputs:** 8x HDMI (HDMI or DVI digital source)
- **Video Outputs:** 4x HDMI : With Booster output 1080p up to 98 feet (30M) & 4K2K up to 66 feet (20M)
- **Audio Support:** Multi Audio Formats 5.1 / 7.1, MAT(MLP), Dolby Digital, Dolby TrueHD, Dolby Digital Plus, DTS, DTS-ES 6CH, DTS-HD, DTS-HD-HRA, DTS-HD Master, (PCM-2CH)
- **Preview Output:** (1) Preview output (same as output #1)
- **Switch Controls:**
 - 1x Select & Function buttons on front panel (Data status via LCM panel show out)
 - 1x IR Remote Controller (switch control)
 - 1x IR External port (switch control via 3.5mm OD Jack)
 - 1x RS-232 series interface (switch control)
 - 1x Ethernet series interface (switch control)
- **Source Status:** Input status LEDs indicates presence of a live signal
- **(18) Function Control Keys:** 1. ALL, 2. OFF, 3. RECALL, 4. ENTER, 5. MEMORY, 6. LOCK, 7. EDID, 8. Destination button 1 thru 4, 9. Source button 1 thru 8
- (7) EDID management:
 - 1. Select Embedded EDID modes: Mode1: FSS, Mode2: H24-3D, Mode3: H24-3D-M, Mode4: H36-3D, Mode5: H36-3D-M, Mode6: 4K2K-3D, PCM-2CH, Mode7: DVI-D 1920x1200-60Hz
 - 2. Select LEARNING mode: Learning Destination EDID to Link Source
- **Infrared Frequency:** 38 Khz
- **IR External Distance:** ~984 feet / 300M maximum
- **Video Booster:** HDMI output 1080p lengths up to 98 feet (30M) / 4K2K up to 66 feet (20M)
- **HDMI I/O Connector:** HDMI Type A - SMD 19pin female Type
- **Temperature:** 32°F - 100°F Operation (0°C - 38°C)
- **Dimensions (LxWxH):** 19 x 9.85 x 1.73 in (482x250x44mm)
- **Rack Mount:** 1RU High 19in Rack Mount #1U-440L (with rack mount)
- **Power Supply:** Power Input : AC 100~240 VAC 50/60Hz (120V/0.5A/60W; 220V/0.27A/60W)
- **Safety Approvals:** CE, FCC, RoHS, REACH
- **Product Weight:** 3.25 Kgs / 7.15 lb

As product improvements are continuous, specifications are subject to change and without notice.

FRONT PANEL

FRONT PANEL



1. POWER SWITCH: The power switch turns the unit on and off and indicates that the switcher is receiving power. The switcher will remember that last state during a power cycle. When power is removed and resorted, the last configuration will be evoked.

2. STATUS DISPLAY: Front panel status display shows current matrix routing configuration. This same display also shows particular configuration settings depending on your current function. In run mode (as shown above), the display shows each Output (destination) channel shows which input (source) is assigned.

3. IR SENSOR: The IR sensor receives IR commands from the supplied remote controller or third party IR emitter.

4. INPUT STATUS DISPLAY: Input sources 1 to 8 LED illuminates blue to indicate that a video source is present on that input.

5. SOURCE SELECT BUTTONS: Separate inputs 1 thru 8 select buttons are provided each source selection.

6. EDID MODE SELECT BUTTONS: Used to select EDID mode using buttons Source button #1 or #2.


7. DESTINATION SELECT BUTTONS: Separate outputs 1 thru 4 select buttons are provided for each destination assignment. Routing can be Source to Destination or one source to multiple destinations.

Example : Press Destination 1,3,4 then press Source 2 will route Input 2 to Output 1,3,4 respectfully.

8. 19 INCH EAR MOUNT PAIR: Converts desktop to 19 inch rack mount. Bracket (part number: 1U-440L) INCLUDED. Image shows rack mount bracket attached.

FRONT PANEL

FRONT PANEL



9. FUNCTION KEY - EDID:



Used to display change current EDID mode.

- Press **EDID** to select new EDID mode or select
- Press **SOURCE** row #1 or #2 Select EDID modes.
- Press **ENTER** to ready memory location.
- Or press **EDID** again to cancel operation.

Operation completes.

Note : Operation will abort if no keys are pressed within 5 seconds.

10. FUNCTION KEY - RECALL:



The system will show previously stored presets, up to a total of 12. Presets are stored in local memory using Source keys 1 thru 8 or Destination keys 1 thru 4 as the memory preset location.

- Press **RECALL** button.
- Press **1 THRU 8** on either Source or **1 THRU 4** on Destination row.
- Press **ENTER** The pre-set configuration will execute.

Operation completes.

Note : Operation will abort if no keys are pressed within 5 seconds.

- or press **RECALL** again to cancel operation.

11. FUNCTION KEY - MEMORY:



The system will show stored presets, up to a total of 12. Presets are stored in local memory using Source keys 1 thru 8 or Destination keys 1 thru 4 as the memory preset location.

- Configure desired matrices.
- Press **MEMORY** button.
- Press **1 THRU 8** on either Source or **1 THRU 8** on Destination row.
- Press **ENTER** to ready memory location.
- or press **MEMORY** again to cancel operation.


Operation completes.

Note: Operation will abort if no keys are pressed within 5 seconds.

- Or press **MEMORY** again to cancel operation.

FRONT PANEL

FRONT PANEL



12. FUNCTION KEY - ALL:



Disables (mutes) video on all destinations OR Selects the same source to all destinations.

Option 1

- Press **ALL** followed by **OFF** button. The display will show " 0 " indicating all destinations have no video selected.

Option 2

- Press **ALL** followed by Source **1 THRU 8**. The display will show the Source selected.
- Press **ENTER**. The pre-set source selection will be assigned all destinations.

13. FUNCTION KEY - OFF:



Disables (mutes) video to selected channels. Either destinations.

- Press **OFF** button followed by any Destination channel.
- Press **1 THRU 8** output destination. The display will show " 0 " for the selected channel indicating no video selected.

14. FUNCTION KEY - LOCK:




- Press and hold **LOCK** button for two seconds lockout the front panel.
- Press and hold **LOCK** button for two seconds to enable the front panel.

15. FUNCTION KEY - ENTER: Press **ENTER** to confirm entries.

BACK PANEL

BACK PANEL



1. POWER INLET: The switcher is fitted with a AC power plug input connector. Ensure that the plug used is of an approved type and is of sufficient current carrying connector capacity with the correct voltage and connector polarity. 100~240Volt AC, 50/60Hz power supply.



POWER SOCKET: Connector Type: IEC 60320 C13

2. IR EXTENDER CONTROL: Supports one IR Extender. Extends a maximum distance of ~984 feet/300M. When you plug the external IR extender into the switcher the front panel IR receiver remains active.

SW IR in




Switch Control

IR EXTENDER JACK: Female Jack - inner OD Ø 3.5 mm

3. RS-232 CONNECTION: RS-232 control port allows for interfacing to a PC, such as a computer or touch panel control, to the switcher via the DB-9pin female connector for serial RS-232 control.

RS232




Switch Control

This port is also for firmware updates.
REMOTE PORT : D-SUB-9pin female connector

4. ETHERNET CONNECTION: ETHERNET control port allows for TCP/IP interfacing to a PC, such as a computer or touch panel control (not a web-browser), to the switcher via this RJ-45 female connector to control switcher.

Ethernet




Switch Control

REMOTE PORT: Control the switcher with the RJ-45 female connector.

ETHERNET PORT: Note: the Ethernet port and RS-232 port **cannot** be used simultaneously. Any connection to the Ethernet port will disable serial commands sent to the RS-232 port.

5. INPUTS 1, 2, 3, 4, 5, 6, 7, & 8 HDMI: Connects a HDMI signal source to the Input. The HDMI ports support HDMI with embedded audio and DVI with AUX audio sources. If you remove the HDMI screw posts, you must use the provided ISO screws to keep the internal HDMI jack secure. Removing the HDMI screws without installing the ISO screws will void your warranty.

HDMI in




HDMI CONNECTOR: HDMI Type A SMD 19pin female socket connector.

Note: With the proper adapters, the switcher can be used with DVI digital video signals, as it is HDCP compliant. DVI supports audio.

6. OUTPUTS- 1, 2, 3 & 4 HDMI: Connects a HDMI signal source to the Output. The HDMI ports support HDMI with embedded audio and DVI with AUX audio. If you remove the HDMI screw posts, you must use the provided ISO screws to keep the internal HDMI jack secure. Removing the HDMI screws without installing the ISO screws will void your warranty.

HDMI out




HDMI CONNECTOR: HDMI Type A SMD 19pin female socket connector.

Note: With the proper adapters, the switcher can be used with DVI digital video signals, as it is HDCP compliant. DVI supports audio.

7. PREVIEW OUTPUT-01 HDMI: Connects a HDMI digital video/audio signal link direct to the HDMI Female connector. This connector supports HDMI digital video/audio and DVI digital video sources. HDMI Preview port signal is the same as Output 1.

Preview output-#1



HDMI DIGITAL VIDEO/AUDIO CONNECTOR: HDMI female connector.

Note: With the proper adapters, the switcher can be used with DVI digital video signals, as it is HDCP compliant. DVI does not support audio.

REMOTE CONTROL

Before making any connections observe the following:

- Ensure the mains voltage supply matches the label on the supplied plug- Pack (+/- 10%).
- Ensure that the power switch is OFF.
- Ensure that all system grounds (earth) are connected to a common point.
- Avoid powering equipment within a system from multiple power sources that may be separated by large distances.
- Connect all audio video sources and destination equipment.
- Power up all source and destination audio-visual sources.
- For each destination output select the appropriate input source by using the front panel input 1-8 select buttons. The supplied IR remote control. Or through the RS-232 serial communications port.
- Upon power up the switcher will return to its last used setting before Powered down.

REMOTE CONTROL

1. & 2. SWITCH POWER ON or OFF:

Controller with a power ON and OFF

3. DESTINATION : 1 THRU 4 OUTPUT SELECTION:

Press the destination button to select the output display channel.


4. SOURCE : 1 THRU 8 INPUT SOURCE SELECTION:

Press input 1~8 sources with selection button

5. FUNCTION KEY: Function selection button

ALL	OFF	EDID
RECALL	MEMORY	ENTER
LOCK		

IR REMOTE : SW-5684K



REMOTE PROTOCOL COMMANDS

IR REMOTE CUSTOM AND DATA CODES (NEC Standard)

HOW TO SETUP IR CODES :

CUSTOM CODE : 1FE0

DATA CODE :

POWER ON	: 1FE0 A15E	LOCK	: 1FE0 B54A
POWER OFF	: 1FE0 A25D	RECALL	: 1FE0 B24D
ALL	: 1FE0 B04F	MEMORY	: 1FE0 B44B
OFF	: 1FE0 B14E	ENTER	: 1FE0 B34C
EDID	: 1FE0 B748		

PRESS TV DESTINATION - # THEN PRES AV SOURCE -

DESTINATION #1 : 1FE0 10EF	SOURCE #1 : 1FE0 01FE
DESTINATION #2 : 1FE0 20DF	SOURCE #2 : 1FE0 02FD
DESTINATION #3 : 1FE0 30EF	SOURCE #3 : 1FE0 03FC
DESTINATION #4 : 1FE0 40DF	SOURCE #4 : 1FE0 04FB

FOR EXAMPLE: SELECT DESTINATION # 1 TO SHOW SOURCE #1~8

The IR Data Code list :

Destination # 1, Source #1	1FE0 10EF 1FE0 01FE
Destination # 1, Source #2	1FE0 10EF 1FE0 02FD
Destination # 1, Source #3	1FE0 10EF 1FE0 03FC
Destination # 1, Source #4	1FE0 10EF 1FE0 04FB
Destination # 1, Source #5	1FE0 10EF 1FE0 05FA
Destination # 1, Source #6	1FE0 10EF 1FE0 06F9
Destination # 1, Source #7	1FE0 10EF 1FE0 07F8
Destination # 1, Source #8	1FE0 10EF 1FE0 08F7

RS-232 & ETHERNET SERIAL INTERFACE

RS-232 SERIAL INTERFACE CONNECT a PC or CONTROL SYSTEM. VERSION COMPATIBLE V2.0



For a complete list of commands, please reference external document extended RS-232 Protocol Instruction Manual.

Example of the commanded string to select Inputs:

Function	Command	Variables
Select source	Source xxx;	xxx = Input Channel (001=Source1, 002=Source2.etc)

Command	Example	Response Description
Source 001;	Source 001#ok;	Select source number 1

RS-232 Pin Diagram



RS-232 CONFIGURATION

RS-232 cable is a straight thru cable and not null-modem

Definition	Pin		Pin	Definition
	1		1	DCD
TX	2	=====	2	RX
RX	3	=====	3	TX
	4		4	DTR
GND	5	=====	5	GND
	6		6	DSR
	7		7	RTS
	8		8	CTS
	9		9	RI



RS-232 SERIAL INTERFACE PROTOCOL COMMANDS (Ethernet / RS-232 Control driver V2.0)


The Shinybow switcher can be controlled via the RS-232 serial control port to allow for interfacing to a PC, or similar third party control system. The serial communication parameters are 9600 baud, 8 bit, No Parity and 1 stop bit - this is often referred to as 9600 8N1. When the unit recognises a complete command it will perform the requested action - there is no delimiter character required.

ETHERNET SERIAL INTERFACE CONNECT a PC or CONTROL SYSTEM. VERSION COMPATIBLE V2.0

ETHERNET SERIAL INTERFACE

Pin	Ethernet	Reference
1	TXOP	TX +
2	TXON	TX -
3	RXIP	RX +
4	NC	
5	NC	
6	RXIN	RX -
7	NC	
8	GND	

Ethernet



Note :
Control the switcher
SPD : Speed
LINK : Ethernet link
RJ-45 Female 8P-8 Connector




For a complete list of commands, please reference external document extended Ethernet Protocol Instruction Manual.

ETHERNET TCP/IP PROTOCOL COMMANDS (Ethernet / RS-232 Control driver V2.0)

*** The Ethernet port and RS-232 port cannot be used simultaneously. Any connection to the Ethernet Control port will disable serial commands send to the RS-232 port. ***








EDID FUNCTION

EDID FUNCTION SETUP

EDID Setup	To change the EDID setup
Step 1 . Press the EDID button	The display will show the currently selected EDID mode
Step 2 . Press SOURCE #1 or #2 button row	The button will flash blue and the display will show the current Embedded EDID Status.
Step 3 . Press the ENTER button	To set EDID mode. The switcher will return to operation mode.
Operation will abort if no keys are pressed within 5 seconds.	
RESET	EDID Return To Factory default
How to RESET EDID mode Press EDID > RECALL > ENTER	RESET to the FACTORY DEFAULT (1080p-2CH). Press EDID button : The LCM will show the current EDID status. Press RECALL button : The LCM will show the RESET EDID. Press ENTER to confirm entries. The EDID will return to FSS [®] mode and resolution 1080p-2CH.
	
	
EDID status	To view the current EDID status.
Step 1 . Press EDID button	The button will flash blue and the display will show the current Embedded EDID Status.
Step 2 . Press EDID button	To exit.
How to setup FSS [®] Function	Fast Speed Start [®]
Step 1 . Press the Destination #1~4 button row Then Press the Source #1~8 button row	To setup and Install all devices.
Step 2 . Press EDID button	Select a optimum status of Embedded EDID mode.
Step 3 . Press ENTER button	To confirm entries.
Step 4 . Press EDID button	To select the EDID FSS [®] mode.
Step 5 . Press ENTER button	To confirm entries.
Embedded EDID modes	Total 7 EDID Modes
Embedded EDID setup Press EDID > SOURCE > ENTER SOURCE #1 or SOURCE #2	To select Embedded EDID mode or LEARNING mode. Press EDID button : The LCM will show the current EDID status. Repeatedly depressing the source 1 button will cycle up thru the options. Repeatedly depressing the source 2 button will cycle down thru the options.
	Embedded EDID : Mode 1 : FSS Mode 2 : H24-3D Mode 3 : H24-3D-M Mode 4 : H36-3D Mode 5 : H36-3D-M Mode 6 : 4K2K Mode 7 : DVI-D 1920x1200-60Hz

EDID FUNCTION

EDID FUNCTION : 7X EMBEDDED EDID MODES

EDID function : 7x Embedded EDID Modes	
Mode 1. FSS[®] (Fast Speed Start) 	Fast Speed Start [®] mode shortens the startup time of the switcher. Selecting this mode does not force the EDID setup to be cancelled. Users may first select one EDID mode from mode 2 to 3, and then select mode 1 for fast speed start.
Mode 2. H24-3D (1080p-24 bits) 	Audio Support : PCM 2CH
Mode 3. H24-3D-M (1080p-24bits) 	Audio Support : MAT(MLP) 7.1CH, PCM 2CH, One Bit Audio 2CH, AC-3 5.1CH, DTS 5.1CH, PCM 7.1CH, Dolby Digital + 7.1CH, DTS-HD 7.1CH
Mode 4. H36-3D (1080p-36 bits) 	Audio Support : PCM 2CH
Mode 5. H36-3D-M (1080p-36 bits) 	Audio Support : MAT(MLP) 7.1CH, PCM 2CH, One Bit Audio 2CH, AC-3 5.1CH, DTS 5.1CH, PCM 7.1CH, Dolby Digital + 7.1CH, DTS-HD 7.1CH
Mode 6. 4K2K (24/30Hz) 	HDMI Support : 4K2K-3D, PCM 2CH (3860x2160-24/30Hz) Audio Support : PCM 2CH
Mode 7. 1920x1200-60Hz (DVI-D) 	DVI Support : DVI-D 1920 x 1200 60Hz

EDID FUNCTION

EDID FUNCTION FOR HDMI MATRIX SWITCHER	
Learning EDID Single to Single	Example : Learn Destination #2 EDID To Source #3.
Step 1 . Press EDID button	The button will flash blue and the display will show the current Embedded EDID Status.
Step 2 . Press the Destination #4 button row	Copy the Destination #4 Display EDID.
Step 3 . Press the Source #5 button row	Learning the Destination #4 EDID to Source # 5.
Step 4 . Press ENTER button	To confirm entries.
Learning EDID Single to multiple	Learning destination EDID link to the majority Sources
Step 1 . Press EDID button	The button will flash blue and the display will show the current Embedded EDID Status.
Step 2 . Press the Destinations #1~4 button row	Copy any 1~4 Destinations EDID.
Step 3 . Press the Source #1~ #8 button row	Learning the Destination EDID link to source #1~#8
Step 4 . Press ENTER button	To confirm entries.
Learning EDID Single to ALL	Learning destination EDID link to All Sources
Step 1 . Press EDID button	The button will flash blue and the display will show the current Embedded EDID Status.
Step 2 . Press Destination button 1 THRU 4	Learning anyone 1~4 Destination EDID to all sources.
Step 3 . Press ALL button	Learning selected destination EDID to all sources.
Step 4 . Press ENTER button	To confirm entries.
SINGLE LEARNING #1 definition	Single Learning EDID from Destination to Source
<ol style="list-style-type: none"> 1. Switcher will LEARN destination EDID and pass the selected source. 2. To set up learning between a single destination and single source: Press EDID button > Press Destination 1 thru 4 > Press Source 1 thru 8 > Press ENTER to confirm. Switcher will learn destination EDID to source device. 3. To set up learning between a single destination and Multiple sources: Press EDID button > Press Destination 1 thru 4 > Press the majority Sources 1 thru 8 > Press ENTER. Switcher will learn single destination EDID to many source devices. 4. How to Learning single destinations with all sources. Press EDID button > Press ALL button > Press ENTER to confirm. 	
MULTIPLE LEARNING #2 definition	Multiple Learning EDID from Destination to Source
<ol style="list-style-type: none"> 1. Switcher will multiple LEARN destination EDID and pass the selected source. 2. To set up multiple learning between a single destination and single source: Press EDID button > Press OFF button > Press Destination 1 thru 4 > Press ENTER to confirm. Switcher will learn destination EDID to source device. 3. When the Source has "Learned" the EDID data from a destination, it will save that EDID information into EPROM and the EDID data will not change. To change a saved HDMI EDID information, you have to select a new LEARNING destination to source or Disable the LEARNING. 	
<p>NOTE : The already learned EDID cannot be modified. You can only rebuild a new Learning EDID.</p> <p>For example; When the Source has "Learned" the EDID data from a destination, It will save that EDID information into EPROM and the EDID data cannot change.</p> <p>Please select new learning destination to sources or change to one of the embedded EDID modes when you want to remove the learning EDID memory from EPRPM.</p>	

EDID FUNCTION

EDID FUNCTION : LEARNING MODES





LEARNING EDID MODE-#1

Learning EDID from Destination to Source

Single Learning Mode#1 EDID setup

Key Press Sequence: EDID > DESTINATION # > SOURCE # > ENTER

The EDID for HDMI has been learned from the Destination port to the Source port.

	<p>1. Press <u>EDID</u> button</p> <p>The LCM will show the current EDID status.</p>
	<p>2. Press <u>DESTINATION (#1 thru #4)</u></p> <p>The LCM will show the LEARNING HDMI. Switcher will LEARN destination HDMI EDID.</p>
	<p>3. Press <u>SOURCE (#1 thru #8)</u></p> <p>Switcher will Learning destination HDMI EDID and pass to the selected source.</p>
	<p>4. Press <u>ENTER</u> to confirm changes.</p> <p>The LCM will return to the default screen showing selected matrix routing status.</p>

NOTE : The already learned EDID cannot be modified. You can only rebuild a new Learning EDID.

For example;

When the Source has “Learned” the EDID data from a destination, It will save that EDID information into EPROM and the EDID data cannot change. Please select new learning destination to sources or change to one of the embedded EDID modes when you want to remove the learning EDID memory from EPROM.





LEARNING EDID #2

Passing EDID from Destination to Source

Multiple Learning mode #2 EDID setup

Key Press Sequence: EDID > OFF > DESTINATION #1 THRU #4 > ENTER


The EDID for HDMI has been Learned from the Destination port to the Source port.

	<p>1. Press <u>EDID</u> button</p> <p>The LCM will show the current EDID status.</p>
	<p>2. Press <u>OFF</u> button</p> <p>The LCM will show the current EDID LEARN status.</p>
	<p>3. Press <u>DESTINATION (#1 thru #4)</u></p> <p>Switcher will LEARN destination HDMI EDID and pass to the selected source. Switcher will Enable or Disable HDMI EDID for the selected source.</p>
	<p>4. Press <u>ENTER</u> to confirm changes.</p> <p>The LCM will return to the default screen showing selected matrix routing status.</p>

NOTE: When the Source has “Learned” the EDID data from a destination, it will save that EDID information into EPROM and the EDID data will not change. To change a saved HDMI EDID information, you have to select a new LEARNING destination to source or Disable the LEARNING.


IR EXTENDER

1. SB-100 IR 300M Receiver



The SB-100 IR Receiver is required when using the port "ALL in" Jack.


2. SB-100C IR 2M Receiver



The SB-100C IR Receiver will not function on the port "ALL in" Jack.


*** When you plug the External IR extender into the switcher, the front panel IR receiver remains active. ***

Pin configuration for IR 984 feet (300M) Extender Receiver such as SB-100 compatible



SB-100 Receiver and SB-101 Transmitter The DISTANCE maximum ~ 984 feet (300M)

Pin configuration for IR Receiver 6 feet (2M) cable such as SB-100C compatible



SB-100 Receiver and SB-101C Transmitter The DISTANCE maximum ~ 984 feet (300M)

Note: The External IR jack has voltage on the "Ring" portion of a 3-conductor plug. You must use a 3-conductor plug (aka: stereo plug). Using a 2-conductor plug will short out the power supply. Always make connections with the switcher power off.

TYPICAL APPLICATION


INSTALLING DIAGRAM

Samples connection :

Using IR External, RS-232 or Ethernet commands to control the SB-5684K via PC or SB-100 IR receiver transmits the SB-5684K's IR signal.

NOTE:

1. Switcher IR External port : Use SB-100 IR signal Receiver.
2. 4K2K Source: Use 4K2K Blu-ray HD Source.
3. Control Switch via a PC RS-232.
4. Control switch via a PC Ethernet.



RS-232 application, IR and Ethernet to control the switcher.

HDBASET™ APPLICATION - TRANSMITTER & RECEIVER

APPLICATION

HDBaseT™ Matrix Switcher using HDBaseT™ Transmitters & Receiver (Sold separately).



SB-6335T5

HDBaseT™ Transmitter with PoE

Distance: Max.100M

INPUTS:

- 1. 1x HDMI source
- 2. 1x F/W update


OUTPUTS:

- 1x HDBaseT™ out

CONTROLS:


- 1x RS-232, 1x IR in, 1x IR out, 1x LAN (Ethernet)

FRONT PANEL :



1. Status via LED Show out : HDCP, Link, Power & PoE
2. 1x Ethernet path to HDBaseT™ Receiver
3. DC Input : 48V, with PoE Transmitter
4. RJ-45 Out : HDBaseT™ signal output to HDBaseT™ Receiver

REAR PANEL :



5. HDMI In : HDMI signal input from HDMI source device
6. IR In : IR signal to HDBaseT™ Receiver
7. IR Out : IR signal from HDBaseT™ Receiver
8. RS-232 i/o : RS-232 series interface control via a PC
9. USB In : F/W Update



SB-6335R5

HDBaseT™ Receiver with PoE

Distance: Max.100M

INPUTS:

- 1. 1x HDBaseT™ In
- 2. 1x F/W update


OUTPUTS:

- 1x HDMI out

CONTROLS:


- 1x RS-232, 1x IR in, 1x IR out, 1x LAN (Ethernet)

FRONT PANEL : HDBaseT 100M Receiver



1. Status via LED Show out : HDCP, Link, Power & PoE
2. 1x Ethernet path to HDBaseT™ Transmitter
3. Extra DC Input : 12V, Transmitter without support Power
4. RJ-45 in : HDBaseT™ signal input from HDBaseT™ Transmitter

REAR PANEL : HDBaseT 100M Receiver



5. HDMI Out : HDMI signal output to destination HDMI device
6. IR In : IR signal to HDBaseT™ Transmitter
7. IR Out : IR signal from HDBaseT™ Transmitter
8. RS-232 i/o : RS-232 series interface control via a PC
9. USB In : F/W Update

Supports HDBaseT™ extenders with a Transmitter and Receiver via HDBaseT™ CATX(6/6a/7) cable.

HDBASET™ APPLICATION

RACKMOUNT (OPTIONAL)


SB-6075A: SB-6335T/R 19 INCH 1RU-1UNIT RACK MOUNT

Model No.: #1U-1p-L440-44MM



SB-6075B: SB-6335T/R 19 INCH 1RU-2UNIT RACK MOUNT

Model No.: #1U-2p-L440-44MM




SB-6069: SB-6335T/R 19 INCH 4U-10P RACK MOUNT

Model No.: #4U-10p-L130MM

SB-6335T/R 4U Ear mount pairs

Parts No.: MEER6069ER13000




HDBASET™ APPLICATION

APPLICATION


Optional 19 inch Rack Mount Bracket for SB-6335T and/or SB-6335R:

Complete 19 inch 4U rack mount of SB-6069
Install Application: SB-6335T/R



SB-6069 (optional) SB-6335TR 19 INCH 4U-10P RACK MOUNT

Model No.: #4U-10p-M130MM
SB-6335T/R 4U Ear mount pairs
Parts No.: MEER6069ER13000




Model No.: #4U-10p-M130MM-COV
SB-6335T/R 4U Ear mount pairs
Parts No.: MEER6069ER11000




SB-6335T/R : Wall mount accessories

Model No.: #WM-1INCH-130MM
SB-6335T/R Wall mount pairs
Parts No.: MEER6335ER11000



Model No.: #4U-10p-M130MM-EAR
SB-6335T/R 4U Ear mount pairs
Parts No.: MEER6335ER11001



Supports HDBaseT™ extenders with a Transmitter and Receiver via HDBaseT™ CATX(6/6a/7) cable.

LIMITED WARRANTY

PLEASE READ THE FOLLOWING TERMS AND CONDITIONS CAREFULLY BEFORE USING THIS HARDWARE, COMPONENTS AND SOFTWARE PROVIDED BY, THROUGH OR UNDER SHINYBOWUSA, INC (COLLECTIVELY, THE "PRODUCT"). By using installing or using the Product, you unconditionally signify your agreement to these Terms and Conditions. If you do not agree to these Terms and Conditions, do not use the Product and return the Product to SHINYBOWUSA, Inc. at the return address set forth on the Product's packing label at your expense. SHINYBOWUSA, Inc. may modify these Terms and Conditions at anytime, without notice to you.

RESTRICTIONS ON USE OF THE PRODUCT

It is your responsibility to read and understand the installation and operation instructions, both verbal and in writing, provided to you with respect to the Product. You are authorized to use the Product solely in connection with such instructions. Any use of the Product not in accordance with such instructions shall void any warranty pertaining to the Product. Any and all damages that may occur in the use of the Product that is not strictly in accordance with such instructions shall be borne by you and you agree to indemnify and hold harmless SHINYBOWUSA, Inc. from and against any such damage.

The Product is protected by certain intellectual property rights owned by or licensed to SHINYBOWUSA. Any intellectual property rights pertaining to the Product are licensed to you by SHINYBOWUSA, Inc. and/or its affiliates, including any manufacturers or distributors of the Product (collectively, "SHINYBOWUSA") for your personal use only, provided that you do not change or delete any proprietary notices that may be provided with respect to the Product.

The Product is sold to you and any use of any associated intellectual property is deemed to be licensed to you by SHINYBOWUSA for your personal use only. SHINYBOWUSA does not transfer either the title or the intellectual property rights to the Product and SHINYBOWUSA retains full and complete title to the intellectual property rights therein. All trademarks and logos are owned by SHINYBOWUSA or its licensors and providers of the Product, and you may not copy or use them in any manner without the prior written consent of SHINYBOWUSA, which consent may be withheld at the sole discretion of SHINYBOWUSA.

The functionality and usability of the Product is controlled by SHINYBOWUSA, Inc. from its offices within the State of Texas, United States of America. SHINYBOWUSA makes no representation that materials pertaining to the Product are appropriate or available for use in other locations other than the shipping address you provided with respect thereto. You are advised that the Product may be subject to U.S. export controls.

DISCLAIMERS AND LIMITATION OF LIABILITY

SHINYBOWUSA may change or modify the Product at any time, from time to time.

THE PRODUCT IS PROVIDED "AS IS" AND WITHOUT WARRANTIES OF ANY KIND EITHER EXPRESS OR IMPLIED. SHINYBOWUSA DOES NOT WARRANT OR MAKE ANY REPRESENTATIONS REGARDING THE USE OR THE RESULTS OF THE USE OF THE PRODUCT'S CORRECTNESS, ACCURACY, RELIABILITY, OR OTHERWISE.

SHINYBOWUSA has no duty or policy to update any information or statements pertaining to the Product and, therefore, such information or statements should not be relied upon as being current as of the date you use the Product. Moreover, any portion of the materials pertaining to the Product may include technical inaccuracies or typographical errors. Changes may be made from time to time without notice with respect to the Product.

TO THE FULLEST EXTENT PERMISSIBLE PURSUANT TO APPLICABLE LAW, SHINYBOWUSA DISCLAIMS ALL WARRANTIES, EXPRESS OR IMPLIED, INCLUDING, BUT NOT LIMITED TO IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE AND NON-INFRINGEMENT. SHINYBOWUSA DOES NOT WARRANT THE ACCURACY, COMPLETENESS OR USEFULNESS OF ANY INFORMATION WITH RESPECT TO THE PRODUCT. SHINYBOWUSA DOES NOT WARRANT THAT THE FUNCTIONS PERTAINING TO THE PRODUCT WILL BE ERROR-FREE, THAT DEFECTS WITH RESPECT TO THE PRODUCT WILL BE CORRECTED, OR THAT THE MATERIALS PERTAINING THERETO ARE FREE OF DEFECTS OR OTHER HARMFUL COMPONENTS. SHINYBOWUSA WILL USE ITS REASONABLE EFFORTS TO CORRECT ANY DEFECTS IN THE PRODUCT UPON TIMELY WRITTEN NOTICE FROM YOU NOT TO EXCEED 10 BUSINESS DAYS AFTER RECEIPT BY YOU OF THE PRODUCT, BUT YOU (AND NOT SHINYBOWUSA) ASSUME THE ENTIRE COST OF ALL NECESSARY SERVICING, REPAIR AND CORRECTION THAT WAS CAUSED BY YOU UNLESS OTHERWISE AGREED TO IN A SEPARATE WRITING BY SHINYBOWUSA.

UNDER NO CIRCUMSTANCES, INCLUDING, BUT NOT LIMITED TO, NEGLIGENCE, SHALL SHINYBOWUSA BE LIABLE FOR ANY SPECIAL OR CONSEQUENTIAL DAMAGES THAT RESULT FROM THE USE OF, OR THE INABILITY TO USE THE PRODUCT IN ACCORDANCE WITH ITS SPECIFICATIONS, EVEN IF SHINYBOWUSA OR ITS REPRESENTATIVES HAVE BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES. IN NO EVENT SHALL SHINYBOWUSA'S TOTAL LIABILITY TO YOU FROM ALL DAMAGES, LOSSES, AND CAUSES OF ACTION (WHETHER IN CONTRACT, OR OTHERWISE) EXCEED THE AMOUNT YOU PAID TO SHINYBOWUSA, IF ANY, FOR THE PRODUCT.

END OF DOCUMENT

THIS PAGE IS INTENTIONALLY LEFT BLANK.

122 Rose Ln. Suite 303 | Frisco, Texas 75034

1-877-SHINY-USA

1-877-744-6987

1-972-377-2508

sales@shinybowusa.com

www.shinybowusa.com

SHINYBOW™ USA
MULTIMEDIA AUDIO AND VISUAL